

## Power Supply Connectors

## APP PC5933T

n. 1

Factory Name	APP PC5933T
Description	Vertical contact MINI P/CLAW APP PC5933T type
Other features	-



## CPE 3 Pole

n. 6

Factory Name	CPE 28-019
Description	HV 3 Pin Panel Male Connector
Other features	supports up to 18 kV



## APP30 1317G4

n. 2

Factory Name	APP30 1317G4 / PP30 1327BK / PP30 1327G6BK
Description	APP30 1317G4 type
Other features	APP30 MOUNTING WINGS 1399G8BK type - Black: PP30 1327G6BK APP - Red: PP30 1327BK APP - Vert. contact PP30 1317G4 APP - Mounting: PP30 MOUNTING WINGS 1399G8BK APP



## CPE HV

n. 7


Factory Name	CPE 23.100.151.046
Description	HV Coaxial Connector
Other features	supports up to 18 kV; mates with HV Cable Connector CPE 23.100.052.045



## AMP 75

n. 3

Factory Name	AMP 201311-3
Description	HV multipin connector
Other features	Mates with AMP 201310 cable connector; suitable for operation in the -55 ÷ +150 °C range



## DB37

n. 8

Factory Name	FCI DCPV37S300GT
Description	DB37 Female connector
Other features	-



## Radiall 52

n. 4


Factory Name	Radiall 691 803 004
Description	HV multipin connector
Other features	Mates with Radiall 691 802 002 and CAEN Mod. A996 cable connectors; up to 9 kV supported



## Brass hexagon head bolt

n. 9

Factory Name	RS Stock no. 483-2390
Description	Brass hexagon head set screw, M6x30mm
Other features	-



## SHV

n. 5

Factory Name	Radiall R317580
Description	HV coaxial connector
Other features	Supports up to 10 kV



## Front - end Connectors

## Robinson Nugent 68 pin boardmount connector

n. 10

Factory Name	3M P50E-068P1-SR1
Description	Robinson Nugent 68 pin straight angle thru-hole boardmount connector
Other features	Mates with: 3M P25E-068S (SY2791) 3M P50E-068S (other modules)



## Header-type connectors

n. 11

Factory Name	3M 3431-6202 (17+17 pin); 3M 3408-5202 (8+8 16 pin)
Description	Header-type connector
Other features	Available with different pin sets; the 17+17 connector mates with 3M 3414-6600 wiremount connector



## LEMO

n. 12

Factory Name	Fischer DP101A004-51
Description	LEMO type coaxial connector
Other features	-



## BNC

n. 13

Factory Name	Radiall R141603
Description	BNC type coaxial connector
Other features	-



## Strip Header

n. 14

Factory Name	AMP 5/826634/0 (17+17 pin)
Description	Male strip header (17+17 pin)
Other features	the 17+17 connector mates with 3M 3414-6600 wiremount connector



## USB

n. 15

Factory Name	AMP 787780-2
Description	USB Type B
Other features	-



## LC

n. 16

Factory Name	Agilent HFBR-5911L/AL
Description	LC type duplex connector
Other features	-



## LEMO EPG0B

n. 17

Factory Name	EPG.0B.302.HLN
Description	LEMO 2 pin type
Other features	-



## MCX connector

n. 18

Factory Name	SUHNER CS 85MCX-50-0-16
Description	50 Ohm MCX connector
Other features	-



## SMC 68 pin connector

n. 19

Factory Name	ERNI SMC-114805
Description	Dual Row 68 pin connectors
Other features	-



## AMP 3 pin connector

n. 20

Factory Name	AMP 3-102203-4
Description	3 pin connector
Other features	-

